



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5803039D
20 - 1000 MHz
70 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5803039D is a 70 Watt broadband amplifier that covers the 20 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5803039D comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	20 – 1000 MHz
2	Saturated Output Power	70 Watts typical
3	Power Output @ 1dB Comp.	30 Watts min
4	Small Signal Gain	+22 dB min
5	Gain Flatness	± 2 dB max
6	IP ₃	+51 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 30 Watts
9	Spurious Signals	< -60 dBc typical @ 30 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	17 Amps max
12	DC Input	28 VDC nominal
13	RF Input	+30 dBm nominal
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
Mechanical		
16	Dimensions (w/Heatsink)	17.5" x 9.8" x 4.1"
17	Weight (w/Heatsink)	22 lbs. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Airflow Required
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



FEATURES:
 Heatsink and Fans Included (Not Shown)



Application Note:
 To achieve full Rated Power for this RF Amplifier the use of a Linear + 27dBm Signal Source/ Driver is recommended, such as the Ophir RF model 5303065 RF Amplifier.